

TLA-101F Preset

ROUTING	A	B	C	D
Model	TLA HF	TLA HF	TLA LF	TLA LF
HP (Type, dB/Oct)	BW24dB	BW24dB	BW24dB	BW24dB
HP Frequency (Hz)	1.8K	1.8K	80	80
LP (Type, dB/Oct)	BW24dB	BW24dB	BW24dB	BW24dB
LP Frequency (Hz)	20K	20K	1.8K	1.8K
Filter 1 Type	PEQ	PEQ	PEQ	PEQ
Filter 1 Freq. (Hz)	2.95K	2.95K	160	160
Filter 1 Oct-BW	0.6	0.6	0.61	0.61
Filter 1 Level (dB)	-2.5	-2.5	2.5	2.5
Filter 2 Type	PEQ	PEQ	PEQ	PEQ
Filter 2 Freq. (Hz)	1800	1800	355	355
Filter 2 Oct-BW	0.55	0.55	0.49	0.49
Filter 2 Level (dB)	-3	-3	-3	-3
Filter 3 Type	PEQ	PEQ	PEQ	PEQ
Filter 3 Freq. (Hz)	5300	5300	850	850
Filter 3 Oct-BW	0.52	0.52	0.49	0.49
Filter 3 Level (dB)	3	3	-2.5	-2.5